


# RLCD-M66H-750

## **TECHNICAL DATA**



# **High Power Red Fiber Coupled Laser Diode**

Rev. 1.1, 11/2019

### **Features**

Output Power: 750 mW660 nm Emission Wavelength

• Spectral Width: ≤3 nm

## **Applications**

- Photo Dynamic Treatment
- Research with visible photo sensitive materials and therapies

## Specifications (25°C)

Туре	Symbol	Min.	Тур.	Max.	Unit
Infrared Laser					
Output Power	$P_{F}$	ı	750	•	mW
Center Wavelength	λς	650	660	670	nm
Spectral Width	Δλ	ı	-	3.0	nm
Threshold Current	I <sub>th</sub>		400		mA
Operation Current	l <sub>op</sub>		1.5		Α
Operation Voltage	V <sub>op</sub>			2.2	V
Package Style		9-Pin HHL			
TEC					
Thermistor Value (25°C)			(10 ±0.5)		ΚΩ
TEC Max. Current			4.0		Α
TEX Max. Voltage			9.8		V
Fiber Characteristics					
Fiber Bundle Diameter		-	105	-	μm
Fiber Numerical Aperature		-	0.22	-	
Fiber Length		-	0.7	-	m
Connector		FC/ST/SMA905			
Absolute Maximum Ratings					
LD Reverse Voltage	Ur		2.0		V
Operating Temperature	T <sub>op</sub>	+10 +20			°C
Storage Temperature	T <sub>stg</sub>	-20 +80			°C
Lead Soldering Temperature (10 sec.)	T <sub>sol</sub>	260			°C

The above specifications are for reference purpose only and subjected to change without prior notice.






# ROITHNER LASERTECHNIK GIRDH

WIEDNER HAUPTSTRASSE 76

1040 VIENNA AUSTRIA TEL. +43 I 586 52 43 -0. FAX. -44. OFFICE@ROITHNER-LASER.COM



## Dimensions (mm)



### Safety of Laser light

Laser Light can damage the human eyes and skin. Do not expose the eye or skin directly to any laser light and/or through optical lens. When handling the LDs, wear appropriate safety glasses to prevent laser light, even any reflections from entering to the eye. Focused laser beam through optical instruments will increase the chance of eye hazard.



### **Cautions**

#### 1. Operating method

- This LD shall change its forward voltage requirement and optical ouput power according to temperature change. Also, the LD will require more operation current to maintain same ouput power as it degrades. In order to maintain output power, use of APC (Automatic Power Control) is recommended. Which use monitor feedback to adjust the operation current.
- Confirm that electrical spike current generated by swithing on and off does not exceed the maximum operating current level specified herein above as absolute maximum rating. Also, employ appropriat countermeasures to reduce chattering and/or overshooting in the circuit.

#### 2. Static Electricity

Static electricity or electrical surges will reduce and degrade the reliability of the LDs. It is recommended to use a wrist trap or anti-electrostatic glove when handeling the product.

### 3. Absolute Maximum Rating

Active layer of LDs shall have high current density and generate high electric field during its operation. In order to prevent excessive damage, the LD must be operated strictly below absolute maximum rating. NOTE

LASERDIODE MUST BE COOLED